## **ANSI B11.8 – 2021**

an American National Standard -

# Safety Requirements for Manual Milling, Drilling and Boring Machines with or without Automatic Control

**ANSI-Accredited Standards Developer and Secretariat:** 



B11 Standards, Inc. POB 690905 Houston, TX 77269, USA

APPROVED: 24 May 2021

by the American National Standards Institute Board of Standards Review



#### COPYRIGHT PROTECTED DOCUMENT

Copyright © 2021 by B11 Standards, Inc.
All rights reserved. Printed in the United States of America
No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of B11 Standards, Inc.

#### **AMERICAN NATIONAL STANDARDS**

By approving this American National Standard, the ANSI Board of Standards Review confirms that the requirements for due process, consensus, balance and openness have been met by B11 Standards, Inc., (the ANSI-accredited standards developing organization). American National Standards are developed through a consensus process. Consensus is established when substantial agreement has been reached by directly and materially affected interests. Substantial agreement means much more than a simple majority, but not necessarily unanimity. Consensus requires that all views and objections be considered, and that a concerted effort be made toward resolution. This process brings together volunteers and/or seeks out the views of persons who have an interest in the topic covered by this publication. While B11 Standards, Inc., administers the process and establishes procedures to promote fairness in the development of consensus, it does not write the document and it does not independently test, evaluate or verify the accuracy or completeness of any information or the soundness of any judgments contained in its standards or guidelines.

American National Standards are promulgated through ANSI for voluntary use; their existence does not in any respect preclude anyone, whether they have approved the standards or not, from manufacturing, marketing, purchasing, or using products, processes, or procedures not conforming to the standards. However, users, distributors, regulatory bodies, certification agencies and others concerned may apply American National Standards as mandatory requirements in commerce and industry.

Neither B11 Standards, Inc. nor any of the organizations or individuals that assisted in authoring, developing, editing or distributing this standard (B11 Standards, Inc. and such organizations and individuals collectively referred to as the "Contributing Parties") makes any warranty, either expressed or implied, as to the fitness of merchantability or accuracy of the information contained within this standard. The Contributing Parties disclaim and make no warranty that the information in this document will fulfill any of your particular purposes or needs. The Contributing Parties disclaim liability for any personal injury, property or other damages of any nature whatsoever, whether special, indirect, consequential or compensatory, directly or indirectly resulting from the publication, use of, application or reliance on this document. The Contributing Parties do not undertake to guarantee the performance of any individual manufacturer or seller's products or services by virtue of this standard or guide, nor does it take any position with respect to the validity of any patent rights asserted in connection with the items which are mentioned in or are the subject of this document. The Contributing Parties disclaim liability for the infringement of any patent resulting from the use of or reliance on this document. Users of this document are expressly advised that determination of the validity of any such patent rights, and the risk of infringement of such rights, is entirely their own responsibility.

In publishing or making this document available, the Contributing Parties are not undertaking to render professional or other services for or on behalf of any person or entity, nor are the Contributing Parties undertaking to perform any duty owed by any person or entity to someone else. Anyone using this document should rely on his or her own independent judgment, or as appropriate, seek the advice of a competent professional in determining the exercise of reasonable care in any given circumstances. In addition to conforming to the requirements of this standard, the responsible personnel must also make an independent determination as to whether a machine, activity or condition complies with the applicable legal requirements in the relevant jurisdiction(s).

B11 Standards, Inc., has no power, nor does it undertake to police or enforce conformance to the requirements of this document. B11 Standards, Inc., does not certify, test or inspect products, designs, or installations for safety or health purposes. Any certification or other statement of conformance to any health or safety-related information in this document shall not be attributable to B11 Standards, Inc., and is solely the responsibility of the certifier or maker of the statement. The American National Standards institute does not develop standards and will in no circumstances give an interpretation of an American National Standard. Moreover, no person shall have the right or authority to issue an interpretation of an American National Standard in the name of the American National Standards Institute. Requests for interpretations should be addressed to the Secretariat (B11 Standards, Inc.).

**NOTICE:** This American National Standard may be revised or withdrawn at any time. The procedures of the American National Standards Institute require that action be taken periodically to reaffirm, revise, or withdraw this standard. You may contact the Secretariat for current status information on this, or other B11 standards.

Published by: B11 Standards, Inc.

POB 690905, Houston, Texas 77269, USA

Copyright © 2021 by B11 Standards, Inc.

All rights reserved. Printed in the United States of America

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

	TABLE of CONTENTS	PAGE
F	OREWORD	VII
E	EFFECTIVE DATE	VII
	CONTEXT (HOW TO READ/USE THIS DOCUMENT)	
	NQUIRIES	
	DEVELOPMENT	
II.	NTRODUCTION	XI
	DRGANIZATION AND APPLICATION OF B11 DOCUMENTS	
1		
	1.1 MANUAL MILLING, DRILLING AND BORING MACHINES	
2	NORMATIVE REFERENCES	
	2.1 INFORMATIVE REFERENCES	2
3		
,	RESPONSIBILITY	
4		
	4.1 SUPPLIER RESPONSIBILITIES	
	4.2 USER RESPONSIBILITIES	
	4.4 PERSONNEL RESPONSIBILITIES	
5		
5		
6	· · · · · · · · · · · · · · · · · · ·	
	6.1 GENERAL REQUIREMENTS	
	6.2 COMPONENT SELECTION	
	6.4 DESCRIPTION OF MODES OF OPERATION	
	6.4.1 General	
	6.5 ELECTRICAL EQUIPMENT	
	6.5.1 Voltage	
	6.5.2 Grounding and shielding	
	6.6.1 Control pressure	
	6.6.2 Circuits with maintained pressure	
	6.6.3 Stopping machine operations	11
	6.6.4 Interruption of pneumatic supply pressure	
	6.6.5 Accumulators	
	6.6.6 Filtering and separating	
	6.7 EXTERNAL POWER SOURCES	
	6.7.1 Fluctuation in or interruption of power sources	
	6.7.2 Isolation of power sources	
	6.8 STORED ENERGY	
	6.9 EXTERNAL INTERFERENCES	
	6.10 PERFORMANCE OF THE SAFETY FUNCTION(S)	
	6.12 STOP AND EMERGENCY STOP CONTROLS	
	6.12.1 General	

	6.12.3	Emergency stop	. 14
	6.13	OPERATOR CONTROL STATIONS	.14
	6.14	MANUALLY OPERATED CONTROL DEVICES	. 14
	6.14.1	General	. 14
	6.14.2		
	6.14.3	· · · · · · · · · · · · · · · · · · ·	
	6.14.4	•	
	6.14.5		
	6.14.6		
	6.14.7		
	6.14.8		
		INDICATORS	. 10
		ANTI-MOTION MECHANISMS OR COUNTER-BALANCE ON SLIDE MECHANISMS	
	6.16.1		
	6.16.2		. 17
	6.16.3		
	6.16.4		
	6.16.5		
		POWER-OPERATED WORKHOLDING	
		COOLANT SYSTEMS	
	6.18.1	Fluid reservoirs	
	6.18.2		
	6.18.3		
	6.18.4		
		TOOL RETENTION	
	6.20	ELIMINATION OF, OR PROTECTION FROM INHERENT HAZARDS	
	6.20.1	Power transmission components	. 19
	6.20.2	Powered moving parts	. 19
	6.20.3		. 19
	6.20.4		
	6.20.5		
	6.20.6		
	6.20.7		.20
		RISK REDUCTION MEASURES	
	6.21.1		
	6.21.2		
	6.21.3		
	6.21.4		
		ACCESS TO MACHINE PARTS	
		STRUCTURAL INTEGRITY	
		NOISE	
		MIST, FUMES, VAPORS AND DUST	
		ERGONOMIC CONSIDERATIONS	
		ENERGY SUPPLY FAILURES	
		ERRORS OF FITTING	
		LIFTING OF MACHINE COMPONENTS	
	0.29	LIFTING OF MACHINE COMPONENTS	. 23
7	LAYO	UT, INSTALLATION, TESTING AND START-UP	.24
-			
		ENERAL	
		YOUT	
		STALLATION	
	7.3.1	Floor loading	
	7.3.2	Anchoring	
	7.3.3	Electrical requirements for installation	
	7.3.4	Control of hazardous energy	. 25
	7.3.5	Lighting	

	7.4	TESTING AND START-UP	26
8	RIS	K REDUCTION MEASURES	27
	8.1	GENERAL	27
	8.2	ENGINEERING CONTROL - GUARDS	27
	8.2.		
	8.2.		
	8.2.		
	8.3	ENGINEERING CONTROL - DEVICES	
	8.3.		
	8.3.		
	8.3	3 Two-hand control used as a engineering control - device(s)	28
	8.4	AWARENESS BARRIERS AND DEVICES	28
	8.5	RISK REDUCTION MEASURES AGAINST SPECIFIC HAZARDS	29
	8.5.		
	8.5.	2 Chip or coolant hazard	29
	8.5.		
	8.6	SAFE WORK PROCEDURES	
	8.7	PERFORMANCE OF THE SAFETY FUNCTION(S)	
	8.8	SPAN OF CONTROL	
	8.8.		
	8.8.		
	8.8.		33
9	SET	Γ UP, OPERATION AND MAINTENANCE	33
J			
	9.1	GENERAL	
	9.2	MACHINE SET-UP PROCEDURES	34
	9.3	OPERATION	
	9.4	MAINTENANCE	
	9.4.		
	9.4.		
	9.5	SUPERVISION	
	9.6	CONTROL OF HAZARDOUS ENERGY	
	9.7	INITIATION OF NORMAL OPERATIONS	
	9.8	SAFETY SIGNS	
	9.9	PERSONAL PROTECTIVE EQUIPMENT (PPE)	38
1	0 T	RAINING	39
	10.1	General	39
	10.1	TRAINING ELEMENTS	
	10.2		
	10.3	OPERATOR TRAINING	
	10.4	MAINTENANCE PERSONNEL TRAINING	
	10.5	SUPERVISOR TRAINING	
	10.6	RETRAINING	
_			
1	1 D	ECOMMISSIONING PROCESS	43
	11.1	Supplier responsibilities	
	11.2	USER RESPONSIBILITIES	
	11.3	Modifier responsibilities	
	11.4	DECOMMISSIONING TASK	
	11.5	CONTROL OF HAZARDOUS ENERGY	
	11.6	LAYOUT	44

ANNEX A - EXAMPLES OF GUARDING OF MANUAL MILLING, DRILLING AND BOMACHINES	
ANNEX B - LIST OF HAZARDS AND HAZARDOUS SITUATIONS	47
ANNEX C - PERFORMANCE OF THE SAFETY FUNCTION(S)	52
ANNEX D – TRAINING	53
LIST OF FIGURES FIGURE 1 — ORGANIZATION OF THE B11 SERIES OF DOCUMENTS	XII
FIGURE 2 – TYPICAL CLAUSE LAYOUT OF B11 BASE STANDARDS	XIII
FIGURE 3 – THE RISK ASSESSMENT PROCESS	8
FIGURE A.1 – HINGED DOOR TYPE GUARD	
FIGURE A.2 – SLIDING DOOR TYPE GUARDS	45
FIGURE A 3 - EXAMPLE OF INTERLOCKED GUARD(S) FOR MANUAL MILLING MACHINES	46

#### **Foreword**

(This foreword is not part of the requirements of American National Standard B11.8-2021)

The primary objective of this standard is to eliminate or control hazards to personnel associated with manual milling, drilling and boring machines by establishing requirements for the construction, operation and maintenance of these machines. To accomplish this objective, responsibilities have been assigned to the supplier (e.g., manufacturer, rebuilder, re-constructor, installer, integrator), the user, and personnel in the working environment.

The words "safe" and "safety" are not absolutes. Safety begins with good design. While the goal of this standard is to eliminate injuries, it is recognized that risk factors cannot be practically reduced to zero in any human activity. This standard is not intended to replace good judgment and personal responsibility. Operator skill, attitude, training, job monotony, fatigue and experience are safety factors that must be considered by the user.

Manual milling, drilling and boring machines, and associated equipment technologies are continuously evolving. This standard reflects the most commonly used and time-tested state of the art at the time of its approval. The inclusion or omission of language relative to any evolving technology, either in the requirements or explanatory area of this standard, in no way infers acceptance or rejection of such technologies.

Inquiries with respect to the application or the substantive requirements of this standard, and suggestions for its improvement are welcomed, and should be sent to B11 Standards, Inc., Attention: B11 Secretariat.

#### **Effective Date**

The following information on effective dates is informative guidance only, and not a normative part of this standard. This Subcommittee recognizes that some period of time after the approval date on the title page of this document is necessary for suppliers and users to develop new designs or modify existing designs or manufacturing processes in order to incorporate the new or revised requirements of this standard into their product development or production system.

This Subcommittee recommends that suppliers complete and implement design changes for new machines and machinery systems within 30 months of the approval date of this standard.

The Subcommittee recommends that users evaluating whether existing machinery and machinery systems implement this edition within 30 months of the approval date of this standard using generally recognized risk assessment methods. If the risk assessment shows that modification(s) is necessary, refer to the requirements of this standard or the machine-specific "base" safety standard to implement risk reduction measures (protective measures) for appropriate risk reduction.

#### Context (how to read/use this document)

The writers of this document understand that the reader/user of this American National Standard is unlikely to read it cover-to-cover but instead (for example), might use the Table of Contents as a sort of 'roadmap' to find a very specific topic and then review *only* that topic. However, the reader/user of this standard is informed that the elements (clauses, subclauses, etc.) of these documents are sequenced and often interrelated in such a way as to state requirements that may very well be dependent on text in a section(s) that precedes the actual requirement. It therefore becomes vital and important for the reader/user of this standard to ensure they understand the depth, range and especially the context of the section or topic in which the actual requirement appears.

#### Inquiries

Inquiries with respect to the application or the substantive requirements of this standard, and suggestions for its improvement are welcomed, and should be sent to the B11 Standards, Inc. POB 690905, Houston, TX 77069 - Attention: B11 Secretariat.

#### Development

This standard was processed and submitted for ANSI approval by the B11 Standards Development Committee (B11 SDC) on safety standards for machines. Committee approval of this standard does not necessarily imply that all committee members voted for its approval. At the time this standard was approved as an American National Standard, the ANSI B11 SDC was composed of the following member organizations:

Alan Metelsky, FS, Eng., Chair / Anne Mathias, PE, Vice-Chair / David Felinski, Secretary

#### **Organizations Represented**

#### Aluminum Extruders Council American Society of Safety Professionals Association for Advancing Automation (A3 Robotics) Association For Manufacturing Technology The Boeing Company

Bridgestone

Canadian Standards Association

Deere & Co. Euchner Exponent FDR Safety

**General Motors Corporation** 

Grantek

Komatsu America Industries

Liberty Mutual MAG Automotive

Metal Powder Industries Federation

National Institute for Occupational Safety & Health Occupational Safety & Health Administration

Omron Automation

Assn. Packaging & Processing Technologies

Pilz Automation Safety, LP Plastics Industry Association Precision Metalforming Association

Presence-sensing Device Manufacturers Association

**Rockwell Automation** 

Safe-T-Sense SICK, Inc.

Sheet Metal & Air Conditioning Contractors Nat'l. Assn.

Toyota Motor Manufacturing North America

#### Name of Representative

#### Delegate Mel Mitchell, CSP Ted Sberna, Sr. Carole Franklin Russ Bensman Rhiannon McPherson Kenji Furukawa, FS Eng Andrea Holbeche, P.Eng. Tony Beeth Ron Yemmans Stephen Andrew, PE Mike Taubitz Mike Douglas Gerald Kupel George Schreck Craig Karasack, CSP Erik Carrier Bill Edwards Rick Current, PE Kenneth Stevanus Tina Hull, FS Exp Bruce Main, PE, CSP Mike Beerman Jeff Linder

James Barrett, Jr. PhD

Michael Poynter, FS Eng

Chris Soranno, FS Exp

Michael McCullion, CSP

James Kirton

Chris Gerges

Chip Boertlein

**Alternate** Bradley Wyatt, CSP Anne Mathias, PE Jeff Fryman Alan Metelsky, FS Eng Mark Ellingson Joey Hinson, FS Eng Walter Veugen Scott Winter Brian Farrell, FS Eng Torsten Skuiins Joe Wolfsberger Stacey Brooks, CSP Patric Brown James Landowski Julie Thompson, CSP Doug Watts James Adams

Mary Bauer, CIH, CSP Frank Webster Tom Egan Doug Sten, PhD, CSP Dale Bartholomew David Klotz Michael Carlson Darin Magnuson, FS Eng Federico Badillo Nate Gose, FS Eng

Rick Di Ioli Andrew Roe, CSP The B11.8 Subcommittee which revised the 2001 standard, had the following members:

Gene Tkachuk, Lamb, Chairman John F. Bloodgood, PE, Secretary Tony Bratkovich, PE Lance Chandler Dennis Coleman, Robert Jewell, Zagar, Inc. Kent Johnson Ralph Lamkin Stephen K. Miller Mark Periello Carl Sharak Warren Stanford William Riley John Wolfe AMT
Boeing
Southwestern
Zagar, Inc.
Deere & Co.
Lovejoy
Bridgeport
Westinghouse
Liberty Mutual
General Motors
U.S. Navy
Sugino Corp.

Since the last revision of ANSI B11.8, the format/style and even some content elements within the ANSI B11 series have evolved. This current revision has maintained many of those same safety requirements and in several instances, updated requirements up-to-date standards of safety practices and technology while updating the format of the standard to the modern B11 standards structure. Additionally, the ANSI B11 series of standards now incorporates the integration of a stratified approach using "types" of standards (i.e., type-A, type-B and type-C standards — see a more detailed explanation of this approach in the Introduction). ANSI B11.8 is considered a type-C standard and is intended to be used (at a minimum) in conjunction with the type-A ANSI B11.0 and type-B ANSI B11.19 (see the B11 documents list on page xi).

The Subcommittee which developed this current revision of ANSI B11.8 had the following members:

Chris Felinski, Chairman, B11 Standards, Inc. David Felinski, Secretary, B11 Standards, Inc. Mike Douglas, General Motors Jim Kirton, Kirton Industrial Equipment LLC Heinz Knackstedt, Machine Control Safety Training Bruce Main, PE, CSP, design safety engineering, inc. Ted Sberna, Sr., White Horse Safety Chris Soranno, FS Eng, SICK, Inc. Mike Taubitz, FDR Safety



### and ANSI B11 conventions

Explanation of the format, This standard uses a two-column format to provide supporting information for requirements. The material in the left column is confined to "Standards Requirements" only, and is so captioned. The right column captioned "Explanatory Information" contains information that the writing Subcommittee believed would help to clarify the requirements contained in the standard. This column should not be construed as being a part of the requirements of this American National Standard. Operating rules (safe practices) are not included in either column of this standard unless they are of such nature as to be vital safety requirements, equal in weight to other requirements, or guides to assist in compliance with the standard.

> As in all American National Standards, the term "SHALL" denotes a requirement that is to be strictly followed in order to conform to this standard; no deviation is permitted. The term "SHOULD" denotes a recommendation, a practice or condition among several alternatives, or a preferred method or course of action.

> Generally speaking, the term "CAN" denotes a possibility, ability or capability, whether physical or causal, and the term "MAY" denotes a permissible course of action within the limits of the standard, however, the terms can often be used interchangeably.

#### **B11 conventions:**

Normative inter-document or intra-document references are denoted by "See #.##." Informative inter-document or intra-document references are denoted by "See also, #.##."

The use of "hard" conversion between metric and English units does not imply a tolerance requirement.

Operating rules (safe practices) are not included in either column of this standard unless they are of such nature as to be vital safety requirements, equal in weight to other requirements, or guides to assist in conformance with the standard.

The ANSI B11 standards generally use the term "OR" as an inclusive disjunction, meaning one or the other or both, but on occasion will use the term "and/or" to emphasize the fact that both are fully intended in cases where the Subcommittee believed it was imperative to make that clear.

A distinction between the terms "individual" and "personnel" is drawn. Individual includes personnel (employees, subcontractors, consultants, or other contract workers under the indirect control of the supplier or user) but also encompasses persons who are not under the direct or indirect control of the supplier or user (e.g., visitors, vendors, etc.).



#### Introduction

The main purpose of every machine tool is to process materials. Inadvertent interference with, or accidental misdirection of the released energy during production, maintenance, commissioning and de-commissioning can result in injury.

The purpose of the ANSI B11 series of machinery safety standards is to devise and propose ways to eliminate or minimize risks of the potential hazards associated with the required tasks. This can be accomplished either by an appropriate machine design or by restricting personnel or other individuals' access to hazard zones, and by devising work procedures to minimize personnel exposure to hazardous situations. This is the essence of the ANSI B11 series of safety standards. This standard recognizes that zero risk does not exist and cannot be attained. However, a good faith approach to risk assessment and risk reduction should achieve an acceptable risk level.

#### **Organization and Application of B11 Documents**

The B11 standards and technical reports can be associated with the ISO "type A-B-C" structure as described immediately below, and as shown in Figure 1.

- **Type-A standards** (basis standards) give basic concepts, principles for design, and general aspects that can be applied to machinery;
- Type-B standards (generic safety standards) deal with one or more safety aspects or one or more types of engineering controls that can be used across a wide range of machinery:
- **Type-C standards** (machinery safety standards) deal with detailed safety requirements for a particular machine or group of machines.

The B11.0 standard on general safety requirements common to ANSI B11 machines is primarily a "type -A" standard in that it applies to a broad array of machines and contains very general requirements. However, in many areas it also contains very specific requirements. B11.19, B11.20, B11.21, B11.25, B11.26, as well as the entire B11 series of Technical Reports are all typical "type-B" documents addressing general safety elements that can be used across a wide range of machinery (such as B11.19 and B11.26) or as a standard when combining machines (B11.20). The B11 series of Technical Reports are informative documents that may be generally applied to many different machines, and as such would fall into the "type-B" category. The machine-specific ("type-C") B11 standards contain detailed safety requirements for a particular machine or group of machines (such as this standard). The type-A B11.0 and the type-C (machine-specific) B11 standards are intended to be used concurrently by the supplier and user of machines. When a type-C standard deviates from one or more provisions dealt with by this standard or by a type-B standard, the type-C standard requirement generally takes precedence. Any deviation in conforming to a requirement of any standard should be carefully evaluated and based on a documented risk assessment.




Figure 1 — Organization of the B11 Series of Documents

An overview of each clause of this standard is provided below (clauses 1 through 3 are not shown in Figure 2, for clarity).

- 1) Scope Provides the boundaries or limits of the standard (i.e., what is/is not included).
- 2) Normative references Other standards which in whole or in part provide additional requirements when referenced in the normative text (i.e., left-hand column of clauses 4 9) of this standard.
- 3) Definitions Terms used in this standard, together with their definitions (terms used in the same context as are generally understood and commonly used in everyday English are not defined).
- 4) Responsibility The general responsibilities of the supplier (builder), user, modifier and the user personnel are listed in clause 4 together with the remaining clauses for which they have primary responsibility.
- 5) Risk assessment process clause 5 presents the general approach to risk assessment (see B11.0 for further explanation of hazard/task identification and risk assessment/risk reduction).
- 6) Design and construction It is assumed that the supplier of new equipment to the user will be responsible for the requirements of clause 6, understanding that the user may add to or modify these requirements through the purchase agreement. For existing machinery, the user is generally responsible for the requirements of clause 6.
- 7) Layout, installation, testing and start-up Although the requirements of clause 7 are predominantly the responsibility of the user, the supplier will normally provide assistance either directly (providing personnel) or indirectly (instruction materials).
- 8) Risk reduction measures This is normally a shared responsibility but often, either the supplier or the user will provide and/or meet the requirements of clause 8.
- 9) Setup, operation and maintenance The user is normally responsible for the requirements of clause 9 with possible assistance from the supplier for training.
- 10) Training The user is normally responsible for the requirements of clause 10 with possible assistance from the supplier for materials or the training itself.
- 11) Decommissioning This is primarily a user responsibility, however, the supplier shares responsibility for taking this aspect into consideration during the design.

#### **Notes for Column Headings in Figure 2:**

**SUPPLIER:** The early stages of a project present the greatest opportunity to determine project requirements and to anticipate and eliminate hazards and hazardous situations.

**MODIFIER:** The entity (OEM, Supplier, or the expert) in that discipline responsible for creating or modifying the system, machinery or equipment, should have all relevant design standards documentation. The entity should begin by working with the end user to list all tasks to achieve an appropriate comprehensive task list base of the "context of use" for the system, machine or equipment.

**USER:** The company representatives (can be from many disciplines) where the system, machinery or equipment will reside during its productive life. They should engage in participating or reviewing the risk assessment and what will be necessary for a final safety buy-off at the final location.

**PERSONNEL:** The group "at risk" from any hazards or hazardous situation presented by the system, machinery, or equipment while performing their tasks to achieve the company's desired productive life. This would include at a minimum, operators, maintenance personnel for both planned and unplanned maintenance, housekeeping and safety representatives. This group would evaluate the engineering controls, complementary measures and administrative controls (see ANSI B11.19). Figure 2 provides an overview of this standard and in particular the responsibilities of and requirements for the supplier, modifier, user, and the user personnel. Numbers in parentheses denote the particular clause or subclause of the standard.




Figure 2 – Typical clause layout of B11 base standards showing the various responsibilities

As of the date of approval of this standard, the ANSI B11 series of American National Standards and Technical Reports on machinery safety consisted of the following documents shown in the list below. The user should check a licensed reseller such as ANSI (www.ansi.org) for the current versions of any of these documents. All archival / historical versions of the documents are available at <a href="https://www.b11standards.org">www.b11standards.org</a>.

List of the Anol BTT Series of Salety Standards and Technical Reports							
#	SHORT TITLE / TOPIC	YEAR	TYPE				
B11.0	Safety of Machinery	2020	Α				
B11.1	Mechanical Power Presses	2009 (R20)	С				
B11.2	Hydraulic & Pneumatic Power Presses	2013	С				
B11.3	Power Press Brakes	2012	C				
B11.4	Shears	2003 (R20)	С				
B11.5	Ironworkers	1988 (R20)	С				
B11.6	Manual Turning Machines w/ or without Auto Control	2001 (R20)	С				
B11.7	Cold Headers and Cold Formers	1995 (R20)	С				
B11.8	Manual Milling, Drilling, & Boring Machines	2001 (R20)	С				
B11.9	Grinding Machines	2010 (R20)	С				
B11.10	Sawing Machines	2003 (R20)	000000				
B11.11	Gear and Spline Cutting Machines	2001 (R12)	С				
B11.12	Roll Forming and Roll Bending Machines	2005 (R20)	С				
B11.13	Single & Multiple-Spindle Automatic Bar and Chucking Machines	1992 (R20)	С				
B11.14	Withdrawn (Coil Slitting Machines; combined into B11.18)	(1996) ´	С				
B11.15	Pipe, Tube and Shape Bending Machines	2001 (R20)	00000				
B11.16	Powder / Metal Compacting Presses	2014 (R20)	C				
B11.17	Horizontal Hydraulic Extrusion Presses	2004 (R20)	С				
B11.18	Machines Processing or Slitting Coiled or Non-Coiled Metal	2006 (R20)	C				
B11.19	Performance Requirements for Risk Reduction Measures (Safeguarding)	2019	B				
B11.20	Integration of Machinery into a System	2017	В				
B11.21	Machine Tools Using Lasers for Processing Materials	2006 (R20)	В				
B11.22	Turning Centers and Automatic Numerically Controlled Turning Machines	2002 (R20)	C				
B11.23	Machining Centers & CNC Milling, Drilling & Boring Machines	2002 (R20)	Č				
B11.24	Transfer Machines	2002 (R20)	Č				
B11.25	Large Machines	2015 (R20)	В				
B11.26	Functional Safety for Equipment / Machine Control Systems	2018	В				
B11.27	Electro-Discharge Machines	2020	С				
B11.TR1	Ergonomics	2016	В				
B11.TR2	Metal Working Fluids	1997 (R16)	В				
B11.TR3	Withdrawn (Risk Assessment / Risk Reduction Guide)	(2000 R15)	В				
B11.TR4	Selection of Programmable Electronic Systems (PES/PLC)	2004 (R15)	В				
B11.TR5	Noise Measurement	2006	В				
B11.TR6	Withdrawn (Safety Control Systems for Machines)	(2010)	В				
B11.TR7	Integration of Lean and Safety	2007 (R17)	В				
B11.TR8	Guide to the Inspection of Risk Reduction Measures	2022	В				
B11.TR9	Cybersecurity	2019	В				
B11.TR10	Guidance on Artificial Intelligence into Machinery Safety Applications	2020	В				
	2100 Safety of machinery (identical adoption of ISO 12100-2010)	2012	Ā				
2012 12:00 20:01, 0:doi.inio/, (doi.inio/, 100 12:00 20:0)							



American National Standard for Machines –

# Safety Requirements for Milling, Drilling, and Boring Machines with or without Automatic Control

**E1** 

#### **STANDARDS REQUIREMENTS**

#### **EXPLANATORY INFORMATION**

(Not part of American National Standard for Machines – Safety Requirements for Milling, Drilling and Boring Machines with or without Automatic Control. (ANSI B11.8-2021).

#### 1 Scope

This American National Standard specifies safety requirements for the design, construction, operation and maintenance (including installation, dismantling and transport) of manually controlled milling, drilling, and boring machines. This standard also applies to devices that are integral to the machine.

These machines may have automatic capability but may not be equipped with automatic tool changing or automatic part handling systems.

This standard applies to various sizes of machines intended to be mounted:

- a) on the floor;
- b) on a foundation; or
- c) on a bench or machine stand.

This standard does not apply to NC milling, drilling and boring machines where manual control is used only to set the machine for automatic production.

See ANSI B11.22 and ANSI B11.23 for the requirements for Machining Centers and Automatic Numerically Controlled Milling, Drilling and Boring Machines.

**Note** – For purposes of this standard, the terms *machine* and *machine tool* refer to manual drilling, milling and boring machines.

## 1.1 Manual Milling, Drilling and Boring Machines

These machines utilize manually initiated steps to produce a part by moving a rotating cutter against a workpiece to remove metal and other materials in milling, drilling and boring operations.